

## 7.0" H.265 4K ALL-IN-ONE NETWORK TESTER

HD H.265 TVI, CVI, AHD, SDI / EX- SDI / SD-SDI MOBILE MINI-NETWORK TESTER

The AVYCON AIVO-70A4K is a 7.0" All-In-One CCTV Network Tester. This tester is compatible with TVI, CVI, AHD, SDI, and Analog. It supports 4K and has a built-in touch screen and Wi-fi capability. The tester is oriented in a handheld style with an included shoulder strap for transport.

## **FUNCTIONS**

- ·7" High Definition Touchscreen, 1920 x 1200 Resolution
- $\cdot$  H.265, H.264, up to 4K video display via IPC Main Stream
- $\cdot$  IP & CVBS (Analog) or HDMI IN & IP Test can be used simultaneously
- $\cdot$  4K Video files and MKV / MP4 formats supported for playback
- $\cdot$  8MP (4K) TVI test, supports up to 3840 x 2160P @ 15FPS
- $\cdot$  8MP (4K) CVI test, supports up to 3840 x 2160P @ 15FPS
- $\cdot$  8MP (4K) AHD test, supports up to 3840 x 2160P @ 15FPS
- · 8MP (4K) EX-SDI & 1080P HD-SDI test
- · HDMI Input supports up to 1080P, outputs up to 4K
- $\cdot$  Up to 4 Channels Rapid ONVIF scan, Auto login, View
- live video, and create camera test reports
- · ONVIF PTZ Control, Video Record and Playback, Screen Snapshot,
- 4x Digital Zoom, Move the image display and Video Output
- · Testerplay™- Display camera stream on tester and
- PC / Mobile Devices simultaneously
- · PoE/DC 12V Output, Input Voltage and Voltage Measurement
- · PoE Input Wattage Tester (15W Max)
- · Ability to install third-party Android apps
- $\cdot$  12 hour battery time, 3-4 hour charging time

## CONTENTS

Unit : inch (mm)



- CCTV Test Meter
- Instruction Manual
- Carrying Case
- Carrying Strap for Case
- Carrying Strap for Meter
- AC Charger
- Test Probe

- BNC to Alligator Clip Cable
- 3.5mm to Alligator Clip Cable
  (2) Conductor Screw Terminal
- to Alligator Clip Cable • BNC Male to BNC Male
- Jumper Cable
- DC to DC Jumper Cable

## **SPECIFICATIONS**

÷

	GENERAL		
LCD	Display Resolution	New 7 inch touch screen with retina display,	
		1920 x 1200 resolution	
		1 Channel BNC input & 1 Channel BNC looped output,	
	CVBS/ RS485	NTSC/PAL (Auto adapt)	
		Analog video level meter, peak video signal level, SYNC signal	
		level, Color bar chroma level measurement	
		PTZ control, RS485 control, Baud 600-115200bps, Compatible	
		with more than 30 protocols such as PELCO-D/P, Samsung, etc	
		CVBS loop test	The tester send and receive color bar
		CVB3 loop test	
		IPC Test/	generator signal, check BNC cable
	IP Camera Test		Can view and control connectected IPC using
		Rapid Video	ONVIF Protocol
		Hik Test Tool	One touch activation for Hikvision camera,
Video Mode			Image test, supports modification of
			username, password and IP parameters
		Dahua Test Tool	Dahua camera test, supports modification of
			username, password, and IP parameters
	IP& CVBS Test	IP & CVBS test at	the same time, converter test from analog to
		digital with dual to	est window
	Coaxial HD Test	8MP TVI camera test, 3840 x 2160P 12.5/15 FPS, UTC control/	
		call OSD menu	
		8MP CVI camera test, 3840 x 2160P 12.5/15 FPS,UTC control/	
		call OSD menu	
		8MP AHD test, 3840x2160P 15 FPS, UTC control/	
		call OSD menu	
		8MP EX-SDI, HD-SDI, 3G-SDI, UTC control & call OSD menu	
	HDMI Input	1 Channel HDMI input, supports 1080P	
	Zoom Image	4x Zoom, to enlarge image, Screen snapshot, Record, Save, View and record and play back	
Analog Video	Colorbar	Output one channel PAL/NTSC color bar video signal for testing	
Output	Generator	monitor or video cable	
		l output, supports 1920 x 1080P	
HDMI Output	12V/3A Power		
		Output DC12V/3A Power out, supplies temporary power for the	
Power Output	Output	camera for testing purposes	
	PoE Power Output	48V PoE Power output, max power 24W	
	RJ45 cable	Test cable pair status, ength, attenuation, reflectivity, impedance,	
Cable Test		lest cable pair sta	tus, ength, attenuation, reflectivity, impedance,
Cable Test	TDR test	skew etc	tus, ength, attenuation, reflectivity, impedance,
Cable Test Testerplay	TDR test	skew etc	
	TDR test Screen Projection: Te	skew etc ster, Android versio	
Testerplay	TDR test Screen Projection: Te Trace route, Link mor	skew etc ster, Android versio iitor, DHCP server, p	n mobile phone and PC display at the same time port flashing, Ping test
Testerplay Network Test	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps	n mobile phone and PC display at the same time port flashing, Ping test , display wireless camera image
Testerplay Network Test Wi-Fi	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps	n mobile phone and PC display at the same time port flashing, Ping test
Testerplay Network Test Wi-Fi Audio Test	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth	n mobile phone and PC display at the same time port flashing, Ping test a, display wireless camera image er sound normal, 1 channel audio signal to
Testerplay Network Test Wi-Fi Audio Test PoE Test	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp	n mobile phone and PC display at the same time port flashing, Ping test a, display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W max
Testerplay Network Test Wi-Fi Audio Test	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp	n mobile phone and PC display at the same time port flashing, Ping test a, display wireless camera image er sound normal, 1 channel audio signal to
Testerplay Network Test Wi-Fi Audio Test PoE Test Drop-down menu	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE any interface	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp	n mobile phone and PC display at the same time port flashing, Ping test a, display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W max
Testerplay Network Test Wi-Fi Audio Test PoE Test Drop-down menu Power Supply	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE any interface DC 12V 3A	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp power switch, IP so	n mobile phone and PC display at the same time port flashing, Ping test , display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W may atting, WLAN switch, HDMI IN functions in
Testerplay Network Test Wi-Fi Audio Test PoE Test Drop-down menu Power Supply Battery	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE any interface DC 12V 3A Built-in 7.4V Lithium p	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp power switch, IP so polymer battery, 75	n mobile phone and PC display at the same time port flashing, Ping test , display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W may atting, WLAN switch, HDMI IN functions in 00mAh
Testerplay Network Test Wi-Fi Audio Test PoE Test Drop-down menu Power Supply Battery Rechargeable	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE any interface DC 12V 3A Built-in 7.4V Lithium 1 3-4 hours of charge ti	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp power switch, IP se polymer battery, 75 me allows up to 12	n mobile phone and PC display at the same time port flashing, Ping test , display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W max atting, WLAN switch, HDMI IN functions in
Testerplay Network Test Wi-Fi Audio Test PoE Test Drop-down menu Power Supply Battery	TDR test Screen Projection: Te Trace route, Link mor Built in Wi-Fi, Speeds 1 Channel audio sign connect headphone Measures PoE switch Allows accessing PoE any interface DC 12V 3A Built-in 7.4V Lithium p	skew etc ster, Android versio itor, DHCP server, p of up to 150 Mbps al input, test wheth or PSE power supp power switch, IP se polymer battery, 75 me allows up to 12	n mobile phone and PC display at the same time port flashing, Ping test , display wireless camera image er sound normal, 1 channel audio signal to ly voltage and cable connection status (15W may atting, WLAN switch, HDMI IN functions in 00mAh



Copyright © AVYCON. All rights reserved. Specifications and pricing are subject to change without notice.

phone: 949-752-7606 email: info@avycon.com social: @avycon\_aivo website: avycon.com